





КОНЕКТОРИ ЗА ЕЛЕКТРИЧЕСКА ВРЪЗКА И АКЕСОАРИ

ТЕХНИЧЕСКИ ПАРАМЕТРИ

Арт.№	Описание	Снимка	Технически параметри
LMSTZK	Захранващ конектор за LED магнитна smart система		Дължина на проводниците: 190 mm Напрежение: max. 48 V DC Ток: max. 4 A (200W)
LMST1SK	Свързващ конектор за LED магнитна smart система		Дължина на проводниците: 20 mm Напрежение: max. 48 V DC Ток: max. 4 A (200W)
LMST2SK	Свързващ конектор за LED магнитна smart система, Гъвкав		Дължина на проводниците: 130 mm Напрежение: max. 48 V DC Ток: max. 4 A (200W)
LMSTCAP	Кутия за захранване/клема		

ОПИСАНИЕ

Конекторите за електрическа връзка в магнитната SMART система UltraLux са на принципа Plug and Play. Всички с изключение захранващия конектор в двата края имат адаптер за релсите на магнитната система. Тяхно свързване е следното: 1)Поставяте щифтовете на адаптера в тоководещите канали на релсата. 2)Магнитът ще помогне допълнително. 3)Натискате страничния бутон за фиксиране върху релсата.

LMSTZK е конектор за захранване на дълбока магнитна шина и шина за вграждане с постоянно 48 V DC. В единият край има проводници, които се свързват към изхода на LED захранване с напрежение 48V DC. В другия край има адаптер за магнитна шина. В този случай на захранване магнитната система губи своята функционалност. Тъй като не може да се регулира напрежението по шините, то и димирането и регулирането на цветната температура е невъзможно. Телата ще излъчват само топла или само студена светлина, в зависимост от поляритета, при който са включени.

LMST1SK е конектор за свързване между две релси, затова дължината на свързващия кабел е малка. В двата края на този конектор има адаптери за магнитна релсова система.

LMST2SK е конектор за свързване между две релси по ъгъл, затова и дължината на свързващия кабел е по-голяма. В двата края на този конектор има адаптери за магнитна релсова система. Използва се в хоризонталните и вертикалните конектори на дълбоките релси и релсите за вграждане в гипсокартон.

LMSTCAP е кутия от полимер. Нейната функция е изцяло естетическа. Тя служи за скриване на електрическата връзка между електрическата инсталация и SMART захранващите модули на магнитната система.

Монтажът на конекторите се извършва при изключено захранващо напрежение.




ЗАПАЗВАНЕ ЧИСТОТАТА НА ОКОЛНАТА СРЕДА

- Продуктът и неговите компоненти не са опасни за околната среда.
- Моля, изхвърляйте елементите на опаковката разделно в контейнерите, предназначени за съответния материал.
- Този продукт не е битов отпадък и потребителят е длъжен да го изхвърля само в контейнери за разделно събиране на излязло от употреба ЕЕО с цел опазване на околната среда и човешкото здраве.



ELECTRICAL CONNECTORS AND ACCESSORIES

TECHNICAL SPECIFICATIONS

Model №	Description	Picture	Technical information
LMSTZK	Power connector for LED magnetic smart system		Wire length: 190 mm Voltage: max. 48 V DC Current: max. 4 A (200W)
LMST1SK	Connector for LED magnetic smart system		Wire length: 20 mm Voltage: max. 48 V DC Current: max. 4 A (200W)
LMST2SK	Flexible connector for LED magnetic smart system		Wire length: 130 mm Voltage: max. 48 V DC Current: max. 4 A (200W)
LMSTCAP	Cover cap for power supply / terminal		

DESCRIPTION

The electrical connectors in the UltraLux SMART magnetic system operate on the Plug and Play principle. All connectors, except for the power connector at both ends, have an adapter for the rails of the magnetic system. Their connection is as follows:

1. Insert the adapter pins into the current-carrying channels of the rail.
2. The magnet will assist with the connection.
3. Press the side button to secure it onto the rail.

LMSTZK is a power connector for a deep magnetic track and a recessed track with a constant 48V DC. One end has wires that connect to the output of an LED power supply with 48V DC. The other end has an adapter for the magnetic track. In this type of power connection, the magnetic system loses its functionality. Since the voltage in the tracks cannot be regulated, dimming and color temperature control are not possible. The fixtures will emit only warm or only cool light, depending on the polarity with which they are connected.

LMST1SK is a connector for linking two tracks, which is why the connecting cable is short. Both ends of this connector have adapters for the magnetic track system.

LMST2SK is a connector for linking two tracks at an angle, hence the longer cable. Both ends of this connector also have adapters for the magnetic track system. It is used in the horizontal and vertical connectors of deep tracks and recessed tracks in drywall.

LMSTCAP is a polymer box. Its function is purely aesthetic. It serves to conceal the electrical connection between the electrical installation and the SMART power modules of the magnetic system.

Installation of the connectors is performed with the supply voltage switched off.

TAKING CARE OF THE NATURAL ENVIRONMENT CLEANLINESS



- The product and its components are not harmful to the environment.
- Please dispose the package elements separately in containers for the corresponding material.
- Please dispose the broken product separately in containers for out of usage electrical equipment.