

Model: DIS1224

DESCRIPTION

The sensor switch turns on, off or adjusts the brightness of the light. This product is a suitable lighting solution for kitchens, furniture, etc.

INSTALLATION

- Clean the installation surface.
- Stick the sensor switch to the desired place.
- Connect the power supply to the switch and the LED strip.
- Use the sensor switch to turn off/on the light or adjust its brightness.

WAY OF WORKING**Switching the lights on or off**



By waving a hand close to the sensor, the light turns on or off.

Adjust the brightness level of the light


The initial brightness level of the LED strip is 50%. By placing a hand close to the sensor the brightness increases or decreases. The minimum brightness level is 10%.

Switch memory

The switch turns on the light at its last brightness level. When there is a power failure, the sensor will turn on the light at 50% brightness.

**TECHNICAL DATA**

Sensor Type	IR
Supply voltage	12 V DC
Maximum output current	2A
Maximum output power	24 W
Dimming range	10% - 100 %
Detection distance	5 cm
Working temperature	-10°C - +40°C
Index of protection	IP20
Dimensions	35/25/10 mm
Detection range	120°

**TAKING CARE OF THE NATURAL ENVIRONMENT CLEANLINESS**

The product and its components are not harmful to the environment.

Please dispose the package elements separately in containers for the corresponding material.

Please dispose the broken product separately in containers for out of usage electrical equipment.

